

## XS1

	Кон.	Цепь
GPMI_D07	1	
NAND_WP0	2	
GPMI_D06	3	
GPMI_D05	4	
GPMI_D04	5	
GPMI_RD	6	
GPMI_CLE	7	
GPMI_ALE	8	
GPMI_D03	9	
GPMI_WR	10	
GPMI_D02	11	
GPMI_D01	12	
NAND_WP1	13	
GPMI_D00	14	
AUART1_CTS	15	
AUART1_RTS	16	
AUART1_RX	17	
AUART1_TX	18	
AUART3_RX	19	
AUART3_TX	20	
AUART3_CTS	21	
AUART3_RTS	22	
GPMI_RDY2	23	
GND	24	
GPMI_CE2	25	
GPMI_CE3	26	
GPMI_RDY3	27	
GPMI_WP	28	
AUART4_RTS	29	
GND	30	
AUART4_RX	31	
AUART4_CTS	32	
JTAG_RTCK	33	
AUART4_TX	34	
JTAG_TRST	35	
JTAG_TDO	36	
JTAG_TMS	37	
JTAG_TDI	38	
USB0DP	39	
JTAG_TCK	40	
USB0DM	41	
GND	42	
VDDXTAL	43	
RTC_VDD	44	
USB1DM	45	
GND	46	
USB1DP	47	
GND	48	
LRADC6	49	
LRADC5	50	
HSADC0	51	
LRADC0	52	
LRADC4	53	
RESETN	54	
SSP0_DETECT	55	
LRADC2	56	
LRADC1	57	
LRADC3	58	
PWRGATE_SSP0	59	
PWRGATE_SSP1	60	
SAIF0_SDATA1	61	
I2C0_SDA	62	
SPDIF	63	
I2C0_SCL	64	
SSP0_DATA1	65	
SSP0_SCK	66	
SSP0_DATA2	67	
SSP0_DATA0	68	
SSP0_DATA5	69	
SSP0_DATA3	70	
SSP0_DATA6	71	
SSP0_DATA4	72	
SSP0_DATA7	73	
SSP0_CMD	74	
GND	75	
GND	76	
VDD5V	77	
VDD5V	78	
DCDC_BAT_BATTERY	79	
PSWITCH_IN	80	

PLLD1.27-80

## XS2

	Кон.	Цепь
LCD_D21	1	
GND	2	
LCD_D23	3	
LCD_D22	4	
LCD_CS	5	
LCD_D18	6	
LCD_D20	7	
LCD_D19	8	
LCD_RD_E	9	
LCD_D15	10	
LCD_D17	11	
LCD_D16	12	
LCD_D13	13	
LCD_D14	14	
LCD_D09	15	
LCD_ENABLE	16	
LCD_D12	17	
LCD_RS	18	
LCD_D11	19	
LCD_D05	20	
LCD_D10	21	
LCD_RESET	22	
LCD_D08	23	
LCD_D07	24	
LCD_D03	25	
LCD_D06	26	
LCD_D01	27	
LCD_DOTCLK	28	
LCD_D04	29	
LCD_D02	30	
LCD_HSYNC	31	
LCD_VSYNC	32	
LCD_D00	33	
LCD_WR_RWN	34	
BACKLIGHT_PWM	35	
PHY0_LED1	36	
GND	37	
PHY0_RX+	38	
GND	39	
PHY0_RX-	40	
GND	41	
PHY0_TX+	42	
GND	43	
PHY0_TX-	44	
DUART_TX	45	
FEC_A3V3_0	46	
AUART0_RTS	47	
DUART_RX	48	
AUART0_TX	49	
AUART0_CTS	50	
SSP2_SS1	51	
AUART0_RX	52	
SSP2_SS2	53	
SSP2_SS0	54	
SSP2_MOSI	55	
SSP2_MISO	56	
AUART2_RTS	57	
SSP2_SCK	58	
AUART2_TX	59	
AUART2_CTS	60	
AUART2_RX	61	
PHY1_LED1	62	
GND	63	
PHY1_RX+	64	
GND	65	
PHY1_RX-	66	
GND	67	
PHY1_TX+	68	
GND	69	
PHY1_TX-	70	
SSP1_DATA3	71	
FEC_A3V3_1	72	
AUART4_CTS_RSV	73	
SSP1_DATA0	74	
AUART4_RX_RSV	75	
SSP1_CMD	76	
AUART4_RTS_RSV	77	
SSP1_SCK	78	
3V3	79	
AUART4_TX_RSV	80	

PLLD1.27-80